

<p>Caller ID - Name and Number (Displays the caller ID info of incoming calls) No star code.</p>	<p>This feature displays to you the name, number, date and time of incoming local and long-distance calls, provided the caller doesn't have ID blocking. Note: the caller's name may or may not appear, depending on what telephone directory he or she appears in. Also, ID information for international calls may not appear.</p> <p>This feature, instead of being turned on or off by you, is programmed into the LISCO switch by our engineers.</p>
<p>Caller ID - Suppress All Calls (Suppresses your caller ID info) No star code.</p>	<p>If the people you call have Caller ID, this feature will prevent them from seeing your name and/or number.</p> <p>This feature, instead of being turned on or off by you, is programmed into the LTDS switch by our engineers.</p>
<p>Caller ID - Suppress Per Call *67</p>	<p>This service blocks Caller ID on a per-call basis.</p> <p>To cause your Caller ID info to be blocked to people you call, pick up your receiver, press *67, then dial the number you want to call. After your call is finished, normal Caller ID will display on future outbound calls.</p>
<p>Call Waiting</p>	<p>Allows you to keep one caller on the line [on hold] while you take a second call, without losing the first call. This feature, instead of being turned on or off by you, is permanently programmed into the LISCO switch.</p> <p>When you are talking on the phone and someone else calls, you will hear a short beep. The new caller will hear the usual ringing. To answer the second call, press the flash button, if available (or the receiver button once firmly and release). You will be connected to the second caller. The first caller is on hold while you are talking to the second caller. To return to the first call, press the receiver button once firmly and release. You can switch back and forth as often as you wish by pressing the receiver button.</p> <p>Ending either call: There are two different ways that one of the conversations you're having can be ended. (1) If you hang up, your phone will ring and you'll be connected with the person remaining on the line. (2) Alternatively, if one of your callers hangs up, just press the receiver button once firmly and release. You will be connected to the other caller.</p>

<p>Call Waiting Cancel - per Call *70</p>	<p>Allows the Call Waiting feature to be disabled for the duration of a telephone call.</p> <p>To cancel Call Waiting: (1) Before placing your call, pick up your receiver and press *70. (2) Listen for a dial tone and dial the phone number as usual. (3) When finished with your call, simply hang up. Call Waiting is automatically reactivated.</p>
<p>Call Forwarding Programmable (all calls) *72 activation, *73 deactivation</p> <p>This feature can be programmed to occur all the time by LISCO Engineers.</p>	<p>Causes all your incoming calls to be redirected to another number. If you are forwarding calls to a non-local number you must dial 1+the area code, and you will incur long distance charges for the duration of the call.</p> <p>To activate, pick up your receiver and dial *72 and then the number to which you want your calls sent. You will hear a beep once you have successfully enabled the service, the phone will then beep busy and can be hung up.</p> <p>To cancel call forwarding, pick up your receiver and press *73, then hang up. Your calls will no longer be forwarded.</p>
<p>Call Forwarding Programmable - Busy *90 activation, *91 deactivation</p> <p>This feature can be programmed to occur all the time by LISCO Engineers.</p>	<p>Causes your incoming calls to be redirected to another number when your number is busy. If you are forwarding calls to a non-local number you must dial 1+the area code, and you will incur long distance charges for the duration of the call.</p> <p>To activate, pick up your receiver and press *90 and then dial the number to which you want your calls sent. You will hear a beep once you have successfully enabled the service, the phone will then beep busy and can be hung up.</p> <p>To cancel call forwarding, pick up your receiver and press *91, then hang up. Your calls will no longer be forwarded.</p>
<p>Call Forwarding Programmable - No Answer *92 activation, *93 deactivation</p> <p>This feature can be programmed to occur all the time by LISCO Engineers.</p>	<p>Causes your incoming calls to be redirected to another number if you don't answer after approximately 36 seconds. (Our engineers can set the delay to anywhere from 1 to 200 seconds. One ring = 6 seconds.) If you are forwarding calls to a non-local number you must dial 1+the area code, and you will incur long distance charges for the duration of the call.</p> <p>To activate, pick up your receiver and press *92 and then dial the number to which you want your calls sent. You will hear a beep once you have successfully enabled the service, the phone will</p>

	<p>then beep busy and can be hung up.</p> <p>To cancel call forwarding, pick up your receiver and press *93, then hang up. Your calls will no longer be forwarded.</p>
3-Way Calling (Conference)	<p>Allows you to talk with two people at the same time on one phone line.</p> <p>To add a third person to your conversation: (1) Press the flash button, if available (or the receiver button) to put the first caller on hold. You'll hear two short beeps followed by a dial tone. (2) Dial the number of the other person you want to add to your conversation. Once the caller answers, you can talk privately before adding the first caller back in. (3) Press the flash/receiver button to bring all three parties on the line.</p> <p>If the third person doesn't answer or the line is busy, press the flash/receiver button twice to cancel.</p> <p>A conversation can be ended in two ways: (1) When either of the parties you're talking to hangs up [in which case, you can continue to talk to the remaining person], or (2) you hang up [which will disconnect all parties].</p>
Hunting	<p>This feature automatically routes incoming calls to a free line. Hunting is placed on individual telephone lines that make up a group, also known as a hunt group. Hunt groups are a series of lines organized so that if the first line is busy the next line is hunted, and so on until a free line is found.</p> <p>This feature, instead of being turned on or off by you, is permanently programmed into the LISCO switch by our engineers.</p>
Speed Dialing One Digit - *74 (Numbers 2-9) Two Digit - *75 (Numbers 20-49)	<p>Works for local, long distance numbers (you must include 1+area code).</p> <p>To set up: Pick up your receiver and press *74 then enter the Speed Dial code (2 through 9) or *75 and the Speed Dial code (20-49). Without a pause, include the complete number you want to assign to that code (so that you are dialing *74###...etc). You will hear a double-beep confirming that the speed dial has been programmed.</p> <p>To dial out, enter the Speed Dial code and the # key.</p>
Automatic Recall	This service allows you to hear the last incoming

***69**

caller's number and then optionally return the call.

To hear the last caller's number, dial *69. To connect to that number, dial "1".

To cancel all outstanding recall attempts, dial *89.